

Use this table to identify the 'type' of TFT display you have,  
Then:-

Use the 'type number' with the Interconnect diagrams  
to fit the appropriate links etc on the TftA PCB.

TftA PCB Connector	TFT Type number:-				
	Type1	Type2	Type2	Type3	Type4

P1 PIN	INNOLUX	POWERTIP	TRULY TFT	AMPIRE	SHARP PSP
1	VLED-	LED K	VLED-	GND	GND
2	VLED+	LED A	VLED+	GND	GND
3	GND	CSB	GND	VCC	VCC
4	VDD	VDDIO	VDD	VCC	VCC
5	R0	R0	R0	R0	R0
6	R1	R1	R1	R1	R1
7	R2	R2	R2	R2	R2
8	R3	R3	R3	R3	R3
9	R4	R4	R4	R4	R4
10	R5	R5	R5	R5	R5
11	R6	R6	R6	R6	R6
12	R7	R7	R7	R7	R7
13	G0	G0	G0	G0	G0
14	G1	G1	G1	G1	G1
15	G2	G2	G2	G2	G2
16	G3	G3	G3	G3	G3
17	G4	G4	G4	G4	G4
18	G5	G5	G5	G5	G5
19	G6	G6	G6	G6	G6
20	G7	G7	G7	G7	G7
21	B0	B0	B0	B0	B0
22	B1	B1	B1	B1	B1
23	B2	B2	B2	B2	B2
24	B3	B3	B3	B3	B3
25	B4	B4	B4	B4	B4
26	B5	B5	B5	B5	B5
27	B6	B6	B6	B6	B6
28	B7	B7	B7	B7	B7
29	GND	GND	GND	GND	GND
30	CLK	CLK	PCLK	CLK	CKL
31	DISP	RESETB	DISP	DISP	DISP
32	NC	HSYNC	HSYNC	Hsync	Hsync
33	NC	VSYNC	VSYNC	Vsync	Vsync
34	DE	SDI	DE	NC	NC
35	NC	SCL	NC	NC	AVDD
36	GND	GND	GND	NC	AVDD
37	XR	XR	X2 R	NC	NC
38	YD	YD	Y1 B	Test1	TEST1
39	XL	XL	X1 L	Test2	TEST2
40	YU	YU	Y2 U	Test3	TEST3

P1b PIN					
1	NONE	NONE	NONE	VLED-	VLED-
2	NONE	NONE	NONE		
3	NONE	NONE	NONE		
4	NONE	NONE	NONE	VLED+	VLED+